

ARG-WL8-HS wireless heat detector with built-in sounder

The wireless heat detector with built-in sounder continuously samples the temperature in the protected area to provide the earliest warning of fire and yet offers a high level of false alarm rejection. An alarm condition is determined when the level of temperature or the thermal variation versus time exceeds the alarm threshold. The well proven adaptive radio signal processing algorithms ensure the highest levels of life safety and system reliability.

Communication between the detector and the translator / repeater modules is wireless, via the "Streletz" bi-directional protocol. Built-in sounder provides notification in case of a fire.

**Features and benefits**

- Maximum, differential, maximum-differential thermal channel
- Bi-directional wireless communication
- Sound synchronization with other sounders
- 10 years battery life
- Self-optimizing wireless frequency and amplitude algorithms
- 5 years product warranty

Technical specifications

Communication range with the translator or repeater (open space)	1200 m
Operating frequency	868 MHz
Modulation type	FSK
Operating frequency channels	6
Sound pressure level	98 dB
Battery life:	
Primary battery (type CR123A)	8-10 years
Secondary battery (type CR123A)	6-12 months
Dimensions (Including adaptor wall base)	110 mm x 64 mm
Weight	200 g
IP rating	IP43
Max tolerated humidity (no condensing)	95% RH
Operating temperature range	From -30 °C to +55 °C

Warranty

All devices are supplied with the benefit of a limited 5 years warranty (the warranty period does not apply to batteries). This warranty is invalidated by mechanical or electrical damage caused in the field by incorrect handling or usage. Product must be returned via your authorized supplier for repair or replacement together with full information on any problem identified.